

INTERLINKING TUCK

Interlinking (or also referred to as daisy chaining) is the process of powering multiple LED fixtures together with a single power supply unit. The LED interlink process utilizes independent switching only, therefore each LED fixture in the interlinked string must be turned on/off individually. When specifying interlinking, the combined fixture wattage must never meet or exceed the wattage capacity of the power supply.

- All interlinked fixtures are controlled by the on/off/dimmer pack on the starter fixture.
- A 65-watt power supply is required when interlinking.
- Total interlinked system wattage cannot exceed 54 watts. Refer to the interlinking combination chart at right for acceptable combinations.
- Do not interlink with any other fixture family.

Interlink Combinations

| 12" | 17" | 31" | 44" |
|-----|-----|-----|-----|
| 6 | 0 | 0 | 0 |
| 5 | 1 | 0 | 0 |
| 5 | 0 | 0 | 0 |
| 4 | 2 | 0 | 0 |
| 4 | 1 | 0 | 0 |
| 4 | 0 | 1 | 0 |
| 4 | 0 | 0 | 0 |
| 3 | 2 | 0 | 0 |
| 3 | 1 | 1 | 0 |
| 3 | 1 | 0 | 0 |
| 3 | 0 | 1 | 0 |
| 3 | 0 | 0 | 1 |
| 3 | 0 | 0 | 0 |
| 2 | 3 | 0 | 0 |
| 2 | 2 | 1 | 0 |
| 2 | 1 | 1 | 0 |
| 2 | 0 | 2 | 0 |
| 2 | 0 | 0 | 1 |
| 1 | 4 | 0 | 0 |
| 1 | 3 | 0 | 0 |
| 1 | 2 | 1 | 0 |
| 1 | 2 | 0 | 1 |
| 1 | 1 | 1 | 0 |
| 1 | 1 | 0 | 1 |
| 0 | 4 | 0 | 0 |
| 0 | 3 | 1 | 0 |
| 0 | 3 | 0 | 0 |
| 0 | 2 | 1 | 0 |
| 0 | 2 | 0 | 1 |
| 0 | 1 | 2 | 0 |
| 0 | 1 | 1 | 1 |
| 0 | 1 | 0 | 1 |
| 0 | 0 | 3 | 0 |
| 0 | 0 | 2 | 0 |
| 0 | 0 | 1 | 1 |
| 0 | 0 | 0 | 2 |